

TECHNICAL DATA

MQ-137 GAS SENSOR

FEATURES

Fast response and High sensitivity

Stable and long life

Simple drive circuit

APPLICATION

They are used in air quality control equipments for buildings/factory, are suitable for detecting of NH_3 .

SPECIFICATIONS

A. Standard work condition

Symbol	Parameter name	Technical condition	Remarks
V_c	Circuit voltage	$5V \pm 0.1$	AC OR DC
V_H	Heating voltage	$5V \pm 0.1$	AC OR DC
R_L	Load resistance	can adjust	
R_H	Heater resistance	$31 \Omega \pm 5\%$	Room Tem
P_H	Heating consumption	less than 800mw	



B. Environment condition

Symbol	Parameter name	Technical condition	Remarks
T_{ao}	Using Tem	$-10^\circ\text{C} - 45^\circ\text{C}$	
T_{as}	Storage Tem	$-20^\circ\text{C} - 70^\circ\text{C}$	
R_H	Related humidity	less than 95% Rh	
O_2	Oxygen concentration	21%(standard condition)Oxygen concentration can affect sensitivity	minimum value is over 2%

C. Sensitivity characteristic

C. Sensitivity characteristics			
Symbol	Parameter name	Technical parameter	Remarks
Ro	Sensing Resistance	900K Ω -4900K Ω (in air)	Detecting concentration scope: 5-200ppm NH ₃
α (20/10) NH ₃	Concentration Slope rate	≤0.65	
Standard Detecting Condition	Temp: 20℃±2℃ Vc:5V±0.1 Humidity: 65%±5% Vh: 5V±0.1		
Preheat time	Over 24 hour		

D. Structure and configuration, basic measuring circuit



Structure and configuration of MQ-137 gas sensor is shown as Fig. 1 (Configuration A or B), sensor composed by micro ceramic tube, sensitive layer, measuring electrode and heater are fixed into a crust made by plastic and stainless steel net. The heater provides necessary work conditions for work of sensitive components. The

enveloped MQ-137 have 6 pins, 4 of them are used to fetch signals, and other 2 are used for providing heating current.

Electric parameter measurement circuit is shown as Fig.2

E. Sensitivity characteristic curve




Fig.3 is shows the typical sensitivity characteristics of the MQ-137 for several gases.

in their: Temp: 20°C、

Humidity: 65%、

O₂ concentration 21%

RL=47k Ω

Ro: sensor resistance
in the clean air.

Rs: sensor resistance at various
concentrations of gases.

Fig.3 sensitivity characteristics of the MQ-137




Fig.4 is shows the typical dependence of the MQ-137 on temperature and humidity.

Ro: sensor resistance at 10ppm of NH₃ at
33%RH and 20 degree.

Rs: sensor resistance at 20ppm of NH₃
at different temperatures and humidity.

SENSITIVITY ADJUSTMENT

Resistance value of MQ-137 is difference to various kinds and various concentration gases. So, When using this components, sensitivity adjustment is very necessary. we recommend that you calibrate the detector for 10ppm NH₃ concentration in air and use value of Load resistance that(R_L) about 47 K Ω (10K Ω to 100K Ω).

When accurately measuring, the proper alarm point for the gas detector should be determined after considering the temperature and humidity influence.



MQ137 Semiconductor Sensor for Ammonia

Sensitive material of MQ137 gas sensor is SnO_2 , which with lower conductivity in clean air. When the target combustible gas exist, The sensor's conductivity is more higher along with the gas concentration rising. Please use simple electrocircuit, Convert change of conductivity to correspond output signal of gas concentration.

MQ137 gas sensor has high sensitivity to Ammonia, also to other organic amine. The sensor could be used to detect different gas which contains Ammonia, it is with low cost and suitable for different application.


Character

- * Good sensitivity to Ammonia
- * Long life and low cost
- * Simple drive circuit

Application

- * Domestic Ammonia detector
- * Industrial Ammonia gas detector
- * Portable gas detector


Configuration



Technical Data

Basic test loop

Model No.			MQ137
Sensor Type			Semiconductor
Standard Encapsulation			Bakelite (Black Bakelite)
Detection Gas			Ammonia
Concentration			5-500ppm (Ammonia)
Circuit	Loop Voltage	V_c	$\leq 24V$ DC
	Heater Voltage	V_H	$5.0V \pm 0.2V$ AC or DC
	Load Resistance	R_L	Adjustable
Character	Heater Resistance	R_H	$31\Omega \pm 3\Omega$ (Room Tem.)
	Heater consumption	P_H	$\leq 900mW$
	Sensing Resistance	R_s	$2K\Omega - 15K\Omega$ (in 50ppm NH_3)
	Sensitivity	S	$R_s(\text{in air})/R_s(5000\text{ppm CH}_4) \geq 5$
	Slope	α	≤ 0.6 ($R_{100\text{ppm}}/R_{50\text{ppm NH}_3}$)
Condition	Tem. Humidity	$20^\circ\text{C} \pm 2^\circ\text{C}$; $65\% \pm 5\% \text{RH}$	
	Standard test circuit	$V_c: 5.0V \pm 0.1V$; $V_H: 5.0V \pm 0.1V$	
	Preheat time	Over 48 hours	



The above is basic test circuit of the sensor. The sensor need to be put 2 voltage, heater voltage (V_H) and test voltage (V_C). V_H used to supply certified working temperature to the sensor, while V_C used to detect voltage (V_{RL}) on load resistance (R_L) whom is in series with sensor. The sensor has light polarity, V_c need DC power. V_C and V_H could use same power circuit with precondition to assure performance of sensor. In order to make the sensor with better performance, suitable R_L value is needed:

$$\text{Power of Sensitivity body}(P_s): P_s = V_c^2 \times R_s / (R_s + R_L)^2$$

Resistance of sensor(R_s): $R_s = (V_c/V_{RL} - 1) \times R_L$

Sensitivity Characteristics




Fig.1 shows the typical sensitivity characteristics of the MQ137, ordinate means resistance ratio of the sensor (R_s/R_0), abscissa is concentration of gases. R_s means resistance in different gases, R_0 means resistance of sensor in 50ppm ethanol. All test are under standard test conditions.

P.S.: Sensitivity to smoke is ignite 10pcs cigarettes in $8m^3$ room, and the output equals to 10ppm NH_3

Influence of Temperature/Humidity





Fig.2 shows the typical temperature and humidity characteristics. Ordinate means resistance ratio of the sensor (R_s/R_0), R_s means resistance of sensor in 50ppm NH_3 under different tem. and humidity. R_0 means resistance of the sensor in environment of 50ppm NH_3 , 20°C/65%RH

Structure and configuration



Structure and configuration of MQ137 gas sensor is shown as Fig. 3, sensor composed by micro Al_2O_3 ceramic tube, Tin Dioxide (SnO_2) sensitive layer, measuring electrode and heater are fixed into a crust made by plastic and stainless steel net. The heater provides necessary work conditions for work of sensitive components. The enveloped MQ-4 have 6 pin, 4 of them are used to fetch signals, and other 2 are used for providing heating current.

Notification

1 Following conditions must be prohibited

1.1 Exposed to organic silicon steam

Organic silicon steam cause sensors invalid, sensors must be avoid exposing to silicon bond, fixture, silicon latex, putty or plastic contain silicon environment

1.2 High Corrosive gas

If the sensors exposed to high concentration corrosive gas (such as H_2S , SO_x , Cl_2 , HCl etc), it will not only result in corrosion of sensors structure, also it cause sincere sensitivity attenuation.

1.3 Alkali, Alkali metals salt, halogen pollution

The sensors performance will be changed badly if sensors be sprayed polluted by alkali metals salt especially brine, or be exposed to halogen such as fluorin.

1.4 Touch water

Sensitivity of the sensors will be reduced when splattered or dipped in water.

1.5 Freezing


Do avoid icing on sensor's surface, otherwise sensor would lose sensitivity.

1.6 Applied voltage higher

Applied voltage on sensor should not be higher than stipulated value, otherwise it cause down-line or heater damaged, and bring on sensors' sensitivity characteristic changed badly.

1.7 Voltage on wrong pins

For 6 pins sensor, if apply voltage on 1、3 pins or 4、6 pins, it will make lead broken, and without signal when apply on 2、4 pins



2 Following conditions must be avoided

2.1 Water Condensation

Indoor conditions, slight water condensation will effect sensors performance lightly. However, if water condensation on sensors surface and keep a certain period, sensor' sensitivity will be decreased.

2.2 Used in high gas concentration

No matter the sensor is electrified or not, if long time placed in high gas concentration, it will affect sensors characteristic.

2.3 Long time storage

The sensors resistance produce reversible drift if it's stored for long time without electrify, this drift is related with storage conditions. Sensors should be stored in airproof without silicon gel bag with clean air. For the sensors with long time storage but no electrify, they need long aging time for stbility before using.

2.4 Long time exposed to adverse environment

No matter the sensors electrified or not, if exposed to adverse environment for long time, such as high humidity, high temperature, or high pollution etc, it will effect the sensors performance badly.

2.5 Vibration

Continual vibration will result in sensors down-lead response then repture. In transportation or assembling line, pneumatic screwdriver/ultrasonic welding machine can lead this vibration.

2.6 Concussion

If sensors meet strong concussion, it may lead its lead wire disconnected.

2.7 Usage

For sensor, handmade welding is optimal way. If use wave crest welding should meet the following conditions:

2.7.1 Soldering flux: Rosin soldering flux contains least chlorine

2.7.2 Speed: 1-2 Meter/ Minute

2.7.3 Warm-up temperature: $100 \pm 20^\circ C$

2.7.4 Welding temperature: $250 \pm 10^\circ C$

2.7.5 1 time pass wave crest welding machine

If disobey the above using terms, sensors sensitivity will be reduced.