

**MS8220R
MS8226T**

3 5/6 TRUE RMS DIGITAL MULTIMETER DIGITAL MULTIMETER



MS8220R 3 5/6 TRUE RMS DIGITAL MULTIMETER

- SMT APPLICATION
- Display: 5999 Counts. Digit is 22mm High
- DC Voltage: 6/60/600V $\pm$ 0.5%, 1000V $\pm$ 0.8%
- AC Voltage: 6/60/600V $\pm$ 0.8%, 1000V $\pm$ 1.0%
- DC Current: 600 μ A/6000 μ A/60mA/600mA $\pm$ 1.2%, 10A $\pm$ 1.5%
- AC Current: 600 μ A/6000 μ A/60mA/600mA $\pm$ 1.5%, 10A $\pm$ 2.0%
- Resistance: 600 Ω /6k Ω /60k Ω /6M Ω $\pm$ 1.0%, 60M Ω $\pm$ 1.5%
- Capacitance: 6nF $\pm$ 1.8%, 60n/600n/6 μ F $\pm$ 1.0%, 60 μ /600 μ /6mF $\pm$ 1.5%
- Frequency: 6000/60k/600k/6M/60MHz $\pm$ 0.5%
- Temperature:
 - 40°C $\sim$ 500°C $\pm$ 2.0%, 501°C $\sim$ 1000°C $\pm$ 2.9;
 - 40°F $\sim$ 932°F $\pm$ 2.0%, 933°F $\sim$ 1832°F $\pm$ 2.9%;
- Diode Test
- Continuity Test
- Autorange And Manual Range
- Data Hold
- Max./Min. Value Measurement
- Auto Power Off
- Power: 6F22(9V)x1
- Size: 195x92x43mm
- Weight: Approx. 380g (including battery)



MS8226T DIGITAL MULTIMETER

- Display 3999 counts
- Relative measurement
- True RMS value
- Auto power off
- Data hold
- RS232C standard interface
- Autorange and manual range
- Back light
- DC Voltage: 400mV/4V/40V/400V $\pm$ 0.5%, 1000V $\pm$ 0.8%
- AC Voltage: 4V/40V/400V $\pm$ 0.8%, 700V $\pm$ 1.2%
- DC Current: 400 μ A/4000 μ A/40mA/400mA $\pm$ 1.2%, 10A $\pm$ 2.0%
- AC Current: 400 μ A/4000 μ A/40mA/400mA $\pm$ 1.5%, 10A $\pm$ 3.0%
- Resistance: 400 Ω /4k Ω /40k Ω /400k Ω /4M Ω $\pm$ 1.0%, 40M Ω $\pm$ 2.0%
- Capacitance: 50nF $\pm$ 5.0%, 500nF/5 μ F/50 μ F/100 μ F $\pm$ 3.0%
- Frequency: 5Hz/50Hz/500Hz/5kHz/50kHz $\pm$ 2.0%
- Duty: 0.1% $\sim$ 99%
- Temperature: -20°C $\sim$ 1000°C
- Continuity test
- Diode test

